

K111 Fuel Pump Driver Control Module

Pin	Size	Color	Circuit	Function	Terminal Type ID	Option
1 - 1	1 - 2.5	1 - RD/VT	1 - 1940	1 - Battery Positive Voltage	1 - I	1 - -
2 - 2	2 - 0.5	2 - GY	2 - 5660	2 - Fuel Pump Controller Data Out Signal	2 - II	2 - -
3	-	-	-	Not Occupied	-	-
4 - 4	4 - 0.5	4 - D-BU/BK	4 - 7493	4 - High Speed GMLAN Serial Data (+)(3)	4 - II	4 - -
5 - 5	5 - 0.5	5 - WH	5 - 7494	5 - High Speed GMLAN Serial Data (-)(3)	5 - II	5 - -
6 - 6	6 - 0.5	6 - VT/L-GN	6 - 439	6 - Run/Crank Ignition 1 Voltage	6 - II	6 - -
7 - 7	7 - 0.5	7 - VT/YE	7 - 5985	7 - Accessory Wakeup Serial Data	7 - II	7 - -
8 - 8	8 - 2.5	8 - GY	8 - 120	8 - Fuel Pump Supply Voltage	8 - I	8 - -
9 - 9	9 - 2.5	9 - BK	9 - 2150	9 - Ground	9 - I	9 - -
10	-	-	-	Not Occupied	-	-
11 - 11	11 - 0.5	11 - D-BU/BK	11 - 7493	11 - High Speed GMLAN Serial Data (+)(3)	11 - II	11 - -
12 - 12	12 - 0.5	12 - D-BU/BK	12 - 7493	12 - High Speed GMLAN Serial Data (+)(3)	12 - II	12 - -
13 - 13	13 - 0.5	13 - WH	13 - 7494	13 - High Speed GMLAN Serial Data (-)(3)	13 - III	13 - -
14 - 14	14 - 0.5	14 - WH	14 - 7494	14 - High Speed GMLAN Serial Data (-)(3)	14 - II	14 - -
15 - 15	15 - 0.5	15 - D-BU	15 - 7444	15 - Fuel System Control Module Shield	15 - II	15 - -
16 - 16	16 - 2.5	16 - BK/L-GN	16 - 1580	16 - Fuel Pump Low Reference	16 - I	16 - -